## **BERNINA**

## *Mastery 7 – Software and the BERNINA 830*

Install Software according the installation directions and an icon is placed on the desktop after installation

- € ArtLink V6 is a free Download from www.berninausa.com>Software>ArtLink6
- € ArtDesign came with earlier 830 purchases. It needs to be updated with SP1 and can be downloaded from www.berninausa.com>Support
- € Version 5 Software needs to be updated with SP2 to have the 830 files added for transferring designs and adding the Jumbo Hoop file. It can be downloaded from www.berninausa.com>Support
- € Version 6 Software needs to be updated with SP1 and can be downloaded from www.berninausa.com>Support

Regardless of the software package type, the transfer of files is the same

Instructions for Converting and transferring Designs to the 830

- 1. Open the design in the software
- 2. Make any changes desired using the tools provided
- 3. Touch the Write to Machine Icon and press OK
- 4. Select either the BERNINA 830 OR the USB Stick for the BERNINA 830
- 5. USB stick Transfer:
  - a. Select the arrow to send the file to the USB Stick
  - b. Wait for the 'Design Successfully sent to the Embroidery System' message
  - c. Take the USB stick to the 830 and embroider the design
- 6. If using the cable, select either the Arrow or the needle to send the file to the 830 directly
  - The Arrow will save the design to the machine memory
  - b. The needle will send the design to the screen and not be permanently saved on the 830



BERNINA Device Selection		X
Select Embroidery System		
⊙ BERNINA 830		
USB stick for BERNINA 830		
O artista 200 / 730		
USB stick for artista 200 (min. Version 4.04) / artista 730 Personal Design Card for artista 200 / 730		
O artista 630 / 640		
USB stick for artista 630 / 640		
O aurora 430 / 435 / 440 / 450		
Memory card for deco 330 / bernette 340 Deco		
artista 165 to artista 185 or Reader / Writer box		
ansta 103 to ansta 103 of fleader / whitei box		
COM Port	Next Start	_
● COM1	Apply these settings (and	
O COM2	suppress this dialog).	
○ сомз		
O COM4	Configuration	
Cancel	OK	